## Wireless Door | Window Sensor



### **Energy Harvesting Wireless Sensor**

As part of Automated Logic's wireless sensing line, Wireless Door | Window sensors are used to detect when windows and doors are opened or closed in a space. Because there are no wires to run, they can be added to your building easily.

Wireless sensors work in conjunction with a wireless adapter, which enables wireless communication between the Wireless sensors and a WebCTRL® BACnet controller in the space. By sensing when windows and doors are opened wirelessly, our WebCTRL controllers can make smart decisions to optimize the control of heating, cooling, and lighting systems in the building, providing optimum occupant comfort and energy efficiency.



### **Key Features and Benefits**

#### **Easy to Install**

- Communicates on the Rnet sensor network, via a wireless adapter
- Can be installed up to 60' away from wireless adapter
- Enables wireless sensing on new or retrofit projects
- Wireless software included for quick & easy sensor pairing
- Available in different frequencies for different parts of the world

#### **Sensing Capabilities**

■ Door or window opening | closing via magnetic relay switch

#### **Automated Logic Wireless System Benefits**

- Wireless and battery-less space sensors (assuming sufficient lighting exists in space)
- Maintenance-free capacitors power the sensors during unlit periods for up to 4-days without a light source
- Easy and cost-effective installation
- No repeaters or amplifiers required for zone-based applications
- Sensors transmit on COV (change of value), to save energy
- Integrates seamlessly with WebCTRL alarming for proactive monitoring of important sensor conditions, including:
  - Sensor backup capacitor charge
  - Sensor signal strength
  - Sensor offline
- Can co-exist on Rnet with Automated Logic's wired ZS sensors
  - Single-program controllers can support a total of 5 sensors
  - Multi-program controllers can support up to 15 sensors





# Wireless Door | Window Sensor

## **Specifications**

Power supply Solar harvesting, internal energy storage

A CR1216 battery is included to supplement power during commissioning and for low-light conditions Supplemental battery option

Customized version of EnOcean® Protocol

Radio frequency 902 MHz (North America)

Transmission range Typically, 60 ft. (18.29 m) maximum from wireless adapter, assuming sensor and wireless adapter are

separated by no more than 1 drop ceiling or 2 walls (drywall with metal studs).

Transmission interval The sensor transmits:

· On change of sensed value, and

· At a regular 25-minute interval (heartbeat).

Maximum operating life

with no light power or battery

Up to 4 days

Minimum illumination strength 15 lux, constant Maximum sensor gap 0.25 in. (6.4 mm)

Degree of protection

Operating environment Indoor rated only, 32° to 131°F (0° to 55°C) 5% to 95% relative humidity (non-condensing)

ABS plastic, ceiling white color Housing

Weight 0.97 oz. (27.5g)

Dimensions Sensor: 3.15"L x 0.83"W x 0.59"D (8.0 cm x 2.1 cm x 1.5 cm)

3.15"L x 0.47"W x 0.5"D (8.0 cm x 1.2 cm x 1.3 cm) Magnet:

FCC CFR47, Chapter 1, Subchapter A, Part 15, Subpart B, Class B Contains Compliance United States of America:

FCC ID: SZV-STM300U

Industry Canada Compliant, ICES-003, Class B Canada:

Contains IC ID: 6713A-STM300U

CE Mark, Low Voltage Directive: 2014/35/EU Europe:

RoHS Compliant: 2011/65/EU

C-Tick Mark, AS/NZS 61000-6-3 Australia and New Zealand:

All trademarks used herein are the property of their respective owners.

1150 Roberts Boulevard, Kennesaw, Georgia 30144 770-429-3000 Fax 770-429-3001 | www.automatedlogic.com

